


PCI Express IDE Adapter Card

1 Port PCI Express IDE Adapter Card

PEX2IDE

Instruction Manual



Actual product may vary from photo

StarTech.com 
Making hard-to-find easy!

FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. Regardless of any direct acknowledgement elsewhere in the body of this document, StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

Table of Contents

Introduction	1
Features	1
System Requirements	1
Package Contents	1
Installation	2
Installing the PCI Express Expansion Card	2
Software Installation	3
Changing the Boot Sequence	3
Specifications	5
Technical Support	5
Warranty Information	5

Introduction

Thank you for purchasing a StarTech.com 1 Port PCI Express IDE Adapter Card. Using the speed and reliability of PCI Express, you will be able to add IDE connectivity to a host computer - a cost-effective way to use legacy devices with more modern computers.

Features

- Provides data burst transfer rates up to 133 MB/s
- Supports ATA/ATAPI Command
- Onboard ROM BIOS provides Boot Features
- One channel IDE support for up to two drives
- Supports PIO Mode 0/1/2/3/4, UDMA 33/66/100
- Supports 48-bit LBA mode over 137Gb

Before you begin

System requirements:

- PCI Express-enabled system with an available PCI Express slot
- Windows® 2000/XP/Server 2003/Windows Vista operating system

Package contents:

This package should contain:


- 1 x PCI-E IDE Adapter Card
- 1 x Internal IDE Cable
- 1 x Instruction Manual

Installation

Installing the PCI Express expansion card




WARNING! PCI Express cards, like all computer equipment, can be severely damaged by static electricity. Be sure that you are properly grounded before opening your computer case or touching your card. StarTech.com recommends that you wear an anti-static strap when installing any computer component. If an anti-static strap is unavailable, discharge yourself of any static electricity build-up by touching a large grounded metal surface (such as the computer case) for several seconds. Also be careful to handle the card by its edges and not the gold connectors.



1. Turn **OFF** the computer power before installation.
2. Remove the chassis cover from your computer.
3. Locate an unused PCI Express slot and remove the corresponding slot cover from rear panel of the computer chassis. Retain the screw (if applicable) used to hold the slot cover in place.
4. Align the PCI Express card with the unused PCI Express expansion slot. Applying pressure evenly across the top edge of the expansion card, firmly but gently insert the card into the slot, ensuring that the card is properly aligned with the rear panel slot.
5. Secure the card to the motherboard and rear chassis, using the screw removed in step 3.

- With the drives secured within the computer case, use the IDE cable provided to connect the Master and Slave devices to the PEX2IDE IDE connector. Please note the orientation of the IDE cable, as illustrated below.



- Replace the chassis cover (removed in step 2).
- Power on the computer and observe the BIOS messages that appear on the monitor. The BIOS will list all Parallel ATA devices attached to the PATA PCI Express Host Adapter. For example:

```
(Copyright Messages)

HDD0: Maxtor 6L080P0      81 GB

Press any key to continue ...
```

If the information displayed on your monitor is correct (all installed devices are listed with the correct device name, etc.), the PATA PCI Express Host Adapter has successfully been installed in your computer.

Software Installation

Because PEX2IDE supports native IDE mode, driver installation is not required. Windows operating systems will detect the card and install the necessary driver automatically.

Changing the Boot Sequence

Changes to the boot sequence of the devices installed in the host computer must be made through the host computer motherboard BIOS setup utility.

- Launch the motherboard BIOS setup utility. Normally, this can be done by pressing the **DEL (DELETE)** key while the BIOS is checking all hardware configurations
- Select **Advanced** BIOS Features

3. Change the **Hard Disk Boot Priority / First Boot Device** to enable the system to boot from the designated drive.
4. Save and exit the BIOS.

Please note that due to variations in BIOS designs, the above instructions may differ from your system BIOS. For further instruction on how to complete this step, please consult the documentation that accompanied your motherboard or computer system purchase.

Specifications

Bus Type	PCI EXPRESS
Connectors	1 x 40 PIN IDC MALE
Cables	18 in internal IDE Cable
OS Support	Windows 2000/XP/2003/VISTA

Technical Support

StarTech.com's lifetime technical support is an integral part of our commitment to provide industry-leading solutions. If you ever need help with your product, visit www.startech.com/support and access our comprehensive selection of online tools, documentation, and downloads.

Warranty Information

This product is backed by a lifetime warranty. In addition, StarTech.com warrants its products against defects in materials and workmanship for the periods noted, following the initial date of purchase. During this period, the products may be returned for repair, or replacement with equivalent products at our discretion. The warranty covers parts and labor costs only. StarTech.com does not warrant its products from defects or damages arising from misuse, abuse, alteration, or normal wear and tear.

Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

About StarTech.com

StarTech.com is “The Professionals’ Source for Hard-to-Find Computer Parts”. Since 1985, we have been providing IT professionals with the quality products they need to complete their solutions. We offer an unmatched selection of computer parts, cables, server management solutions and A/V products and serve a worldwide market through our locations in the United States, Canada, the United Kingdom and Taiwan.

Visit **www.startech.com** for complete information about all our products and to access exclusive interactive tools such as the Parts Finder and the KVM Reference Guide. StarTech.com makes it easy to complete almost any IT solution. Find out for yourself why our products lead the industry in performance, support, and value.